


MPSR220V10



StartBox - Standard



- This StartBox variation protects the pump motor from damage due to over amping while still performing all the basic function of the standard pump start relay.
- Provides the pump motor with thermal overload protection, even when the motor itself does not
- Auto-resets upon cool-down
- For use with single phase motors
- Reduced incoming amperage option available

Construction

- Quick-connect terminals
- UL listed relay
- NEMA 3R UL listed enclosure - approved for outdoor use, available in stainless steel or powder coated blue or grey

Specifications

- Line Voltage: 220v
- Control Voltage: 220v
- HP: 10
- Amp Range: 34 - 50
- Hertz: 60
- Dimensions: 12"x12"x6"





8 To Controller
Master Valve (Black)

7 To Controller
Common (White)

3 to L1

5L3 to 4T2

5 to 95



*Knockouts



230V Power to 1L1 and
230V Power to 3L2

2T1 to Motor Line 1
and 6T3 To Motor Line 2

Ground Wire

*All Wires Leaving Box Through Knockouts in Base

munro MPSR220V10 Controller