


MPSR220V3



StartBox - Standard




- This StartBox variation protects the pump motor from damage due to over amping while still performing all the basic function of the standard pump start relay.
- Provides the pump motor with thermal overload protection, even when the motor itself does not
- Auto-resets upon cool-down
- For use with single phase motors
- Reduced incoming amperage option available

Construction

- Quick-connect terminals
- UL listed relay
- NEMA 3R UL listed enclosure - approved for outdoor use, available in stainless steel or powder coated blue or grey

Specifications

- Line Voltage: 220v
- Control Voltage: 220v
- HP: 3
- Amp Range: 14.7 - 15.6
- Hertz: 60
- Dimensions: 8"x8"x4"



*Knockouts

7 to Control Device
Common (White)

8 to Control Device
Master Valve (Black)

5 to AC402
Left Side

OL Relay
to AC402
Right Side

220V Power to 1 L1 and
220V Power to 3 L2

OL Relay to Motor Line 2

1 T1 to Motor Line 1

Ground Wire

* All Wires Leaving Box Through Knockouts in Base

MUNRO MPSR220V3 Pump Start Relay