


MPSR24V10



StartBox - Standard




- This StartBox variation protects the pump motor from damage due to over amping while still performing all the basic function of the standard pump start relay.
- Provides the pump motor with thermal overload protection, even when the motor itself does not
- Auto-resets upon cool-down
- For use with single phase motors
- Reduced incoming amperage option available

Construction

- Quick-connect terminals
- UL listed relay
- NEMA 3R UL listed enclosure - approved for outdoor use, available in stainless steel or powder coated blue or grey

Specifications

- Line Voltage: 110/220v
- Control Voltage: 24v
- HP: 10
- Amp Range: 34 - 50
- Hertz: 60
- Dimensions: 12"x12"x6"



*Knockouts

8 To Controller Master Valve (Black)
7 To Controller Common (White)

*All Wires Leaving Box Through Knockouts in Base

230V Power to 1L1 and 230V Power to 3L2
2T1 to Motor Line 1 and 6T3 To Motor Line 2
Ground Wire

MUNRO MPSR24V10 Controller