

MPSR220V5

StartBox - Standard

- This StartBox variation protects the pump motor from damage due to over amping while still performing all the basic function of the standard pump start relay.
- Provides the pump motor with thermal overload protection, even when the motor itself does not
- Auto-resets upon cool-down
- For use with single phase motors
- Reduced incoming amperage option available



Construction

- Quick-connect terminals
- UL listed relay
- NEMA 3R UL listed enclosure - approved for outdoor use, available in stainless steel or powder coated blue or grey


Specifications

- Line Voltage: 220v
- Control Voltage: 220v
- HP: 5
- Amp Range: 24.1 - 25.9
- Hertz: 60
- Dimensions: 8"x8"x4"

MUNRO MPSR220V5 Pump Start Relay



*Knockouts



* All Wires Leaving Box Through Knockouts in Base

MUNRO MPSR220V5 Pump Start Relay